

RCB Controlbox – Mobile Turnstile Premium

	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22
L	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44

Power

L – Line

(x – x)

N – Neutral

100-240 Vac

50-60 Hz

Outside/Entry card reader 1A

9 – Black/GND

10 – Red/24Vdc

11 – Grey

12 – Pink

13 – Blue

14 – Brown

15 – Yellow

Inside/Exit

card reader 2A

16 – Black/GND

17 – Red/24Vdc

18 – Grey

19 – Pink

20 – Blue

21 – Brown

22 – Yellow

Controlbox	PLC	Signal
3. Black	6	GND (Common)
5. Yellow	3 (INP3)	Entry (NO)
6. Blue	6	GND (COMMON)
8. Grey	2 (INP2)	Exit (NO)
38. Brown	7	GND (Common)
36. Green	11 (OUT4)	Entry Sensor (NO)
43. White	10 (OUT3)	Exit Sensor (NO)



The installation must allow an emergency evacuation in case of fire, power failure and other hazards!

Please note that local laws and regulations may apply.

infobric.