

RCB Controlbox – Mobile Turnstile Pro

		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22
L	N	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44

Power

L – Line

(x – x)

N – Neutral

100-240 Vac

50-60 Hz

**Outside/Entry
card reader 1A**

9 – Black/GND

10 – Red/24Vdc

11 – Grey

12 – Pink

13 – Blue

14 – Brown

15 – Yellow

Inside/Exit

card reader 2A

16 – Black/GND

17 – Red/24Vdc

18 – Grey

19 – Pink

20 – Blue

21 – Brown

22 – Yellow

Controlbox	PLC	Signal
3. Blue	16	GND
5. Blue/White	9 (S1)	Entry (NO)
6. Orange	16	GND
8. Orange/White	10 (S2)	Exit (NO)
38. Brown	17	GND
36. Green	18	Entry Sensor (NO)
43. Brown/White	19	Exit Sensor (NO)



The installation must allow an emergency evacuation in case of fire, power failure and other hazards!

Please note that local laws and regulations may apply.